


UXP-NM-12

N Male Connector for 1/2" Annular Cable



[Installation video](#)



[Installation instructions](#)



Contact technical support:
1-888-201-6073
techsupport@jmawireless.com

General	Specification			
Interface/gender	N male			
Cables supported¹	JMA Wireless	JMA12-50	Eupen	EC4
	CommScope	LDF4		LS/Superior Essex
		LDF4RK	HFC 12D	
		LDF4 RN	HFAC 12D	
	RFS	LCF12	Hansen	RF5012
		LCF12-50JL		RF5012Z
	NK Draka	RFA1200	Belden	RA500
Rosenberger	SL 1/2" R	RA500R		
Wireless Supply	WS12			
Weight	0.261 lb 118.4 g	JMA Weather Protection System	WPS-N-4A	

Tools required	JMA part number	Comment
Cable preparation	SP-1/2-LDF4D	"U" bit
Connector compression	HCG-FRAMESET-1/2, HCG-CC	Insert B
Torque wrench	TW1412	14 lbf·in 1.58 N·m

Frequency band	VSWR	Return loss (dB)
555–1000 MHz (0-1 GHz)	1.02	40
1000–2700 MHz (1-2 GHz)	1.03	38
2700–3800 MHz (2-4 GHz)	1.05	30
3800–6000 MHz (4-6 GHz)	1.08	26

Electrical	Specification	Comment
Connector impedance	50 ohm	
Operating frequency band	DC–6 GHz	
3rd order IMD dynamic, (PIM)	-161 dBc, typical	IEC 62037-2
DC test voltage	2000 V	
Center contact resistance	≤ 01.5 milliohm	
Outer contact continuity	0.3 milliohm max.	
Average power	600 W @ 900 MHz	
Peak power, max.	10 kW	
Insertion loss, typical	0.05 dB	Per connector
Shielding effectiveness	< -120 dB	@ 0-1 GHz

Mechanical	Specification	Comment
Pull force combined	1.1 kN >250 lb	Cable limited
Cable retention torque	6.7 N·m 5 lbf·ft	Cable limited
Interface durability	500 cycles	IEC 61169-4:9.5

Environmental	Specification	Test
Operating temperature	-55 °C to +85 °C (-67 °F to 185 °F)	
Storage temperature	-55 °C to +85 °C (-67 °F to 185 °F)	
Accelerated UV	1000 hr	ASTM G154
Immersion test method	Mated & unmated, IP68	IEC 60529:2001 & ANSI/SCTE 60
Water jetting test method	Mated & unmated, IP66	IEC 60529:2001
Mechanical shock test method	Pass	IEC 60068-2-27
Thermal shock test method	Pass	IEC 60068-2-14
Vibration test method	100 m/s ² , 2 Hz to 200 Hz	IEC 61169-1:2003
Corrosion test method	1000 hr	IEC 60068-2-11

¹For cable types not listed, please contact JMA Technical Support.